

Product Spec Sheet from Rentex

QSC TouchMix-16 Compact Digital Mixer with Touchscreen

Download Spec Sheet @ www.rentex.com/spec/MXR1620.pdf

Rentex Product No. MXR1620



Mfr Part No. TOUCHMIX-16

The TouchMix-16 Compact Digital Mixer with Touchscreen from QSC is a 20-input digital mixer that features 16 built-in mic preamplifiers and can be controlled by its integrated touchscreen or wirelessly via an iPad connected to the same wireless network. The mixer features a DSP-based 4-band parametric EQ with variable high- and low-pass filters, a gate, and compressor on each input channel.

Features

- 20 total inputs: 16 mic, (four with XLR/TRS combo connector) and two stereo line (TRS)
- Dedicated talkback mic input
- Stereo Main L/R outputs (XLR)
- Ample monitor outputs (eight total) with 6 mono auxiliary mixes (XLR) and 2 stereo auxiliary mixes

Detailed Specifications

Display	6.1 x 3.5" (156 x 90 mm) color TFT, touch sensing	Mic & Line Input Processing	4-band parametric EQ with Hi/Low shelving option Variable 24 dB/octave HPF & LPF Gate Compressor
Recording	20 tracks, requires USB 3.0 Hard Drive, minimum 7800 RPM	2-Track (USB) & FX Return Processing	2-band shelving EQ Variable 24 dB/octave HPF Gate Compressor
Groups	8 DCA groups (with mutes) 8 Mute groups	Output Channel Processing	Main Output & Auxes 1 to 6: 1/3 octave graphic EQ, variable HPF & LPF, 4-band variable notch filter, limiter Auxes 7/8, 9/10: 4-band parametric EQ, limiter
Cue	Input priority cue, AFL, PFL, Solo in place	Sampling Frequency	44.1/48 kHz
Effects	Reverb, echo, delay, chorus 1x Pitch Correct (assignable to any mono input channel) 50x factory presets 50x user presets	Internal Processing	32-bit floating point
Crosstalk	-80 dB	Frequency Response	20 Hz to 20 kHz, +/-0.5 dB, any input to any output
Max Input Level	+16 dB (Mic inputs) +22 dB (Line inputs)	Signal to Noise Ratio	94 dB
Wi-Fi	USB Wi-Fi adapter included	Output Noise	Residual Output Noise: -86 dBu
Dynamic Range	105 dB	Line Voltage	100 V AC - 240 V AC, 50 - 60 Hz
EIN	-128 dBu	Control	External Control: iOS mixer app for iPad, control via Wi-Fi provides access to all mixer functions
Input	20x Total 4x Combo XLR/TRS 12x XLR 2x Stereo 1/4" (6.3 mm) TRS 1x XLR talkback	Phantom Power	48 V, individually switchable per channel
Output	2x Main XLR, line level 6x Aux XLR, line level 2x Stereo Aux TRS (line or ear monitors, 16 Ω minimum impedance) 1x Stereo monitor TRS (line or headphone, 16 Ω minimum impedance) 1x Stereo cue TRS (line or headphone, 16 Ω minimum impedance)	Dimensions	14.2 x 3.5 x 11.7" (WxHxD)
		Weight	5.9 lb (2.98 kg)