

# Product Spec Sheet from Rentex

## Yamaha QL1 32-Channel Digital Mixer



Mfr Part No. QL1  
Rentex Product No. MXR3210

Packed with many of the core features of their acclaimed CL Series, the Yamaha QL1 32-channel digital mixer is your ideal compact all-in-one solution for mixing, processing, and routing audio. Loaded with premium internal processors, including stellar-sounding EQ and dynamics tools developed in cooperation with Rupert Neve Designs, the QL1 will bring out the best sonic character in any source. With built-in automixing functionality, Dante network support, and remote control via your tablet or computer, the Yamaha QL1 is the perfect sound reinforcement solution for small- to medium-scale live sound, corporate speech events, broadcast, and more!

### Features

- Pure, natural sound and powerful processing
- Revolutionary Dan Dugan automatic mixer
- Refined Control for Smooth Operation
- Link it up with built-in Dante networking

### Detailed Specifications

Input Mixing Channels	32 mono + 8 stereo
Inputs - Mic Preamps	16 x XLR
Phantom Power	16 x Channels
Fader	18 x 100mm Throw
Inputs - Digital	2 x EtherCon Cat5 (Dante Primary, Secondary)
Outputs - Main	1 x XLR (AES/EBU), 2 x EtherCon Cat5 (Dante Primary, Secondary)
MIDI I/O	In, Out
Data I/O	Network RJ-45, GPI
Busses/Groups	16 mix, 8 matrix
I/O Expansion Slots	2 x Slots (mini-YGDAI)
EQ Bands	4-band Parametric
Height	10.7"
Depth	22.1"
Width	18.4"
Weight	32.4 lbs.