



**Mfr No. 505453**

**Rentex No. MIC0700**

The MKE 600 is the ideal video camera/camcorder microphone able to handle even demanding filmic challenges. Due to its high directivity, the MKE 600 picks up sounds coming from the direction in which the camera is pointing and effectively attenuates noise coming from the sides and rear. The switchable "Low Cut" filter additionally minimizes wind noise. Because some video cameras/camcorders do not provide phantom power, the MKE 600 can also be battery powered. A battery on/off switch prevents the battery from discharging prematurely; "Low Batt" is displayed.

Form Factor	Stand/Boom Mount
Sound Field	Mono
Operating Principle	Line Gradient
Output Connectors (Analog)	1 x XLR 3-Pin
Capsule	Condenser
Polar Pattern	Lobar, Supercardioid
High-Pass Filter	100 Hz
Operating Voltage	48 V ± 4 V
Frequency Range	40 Hz to 20 kHz
Maximum SPL	132 dB SPL (Phantom Power) 126 dB SPL (Battery Power)
Operating Current Consumption	4.4 mA (Phantom Power)
Battery Type	1 x AA
Approximate Battery Life	150 Hours
Dimensions	∅: 0.79 x L: 10.08" / ∅: 20 x L: 256 mm
Weight	4.52 oz / 128 g (Microphone)

## FEATURES

- Pronounced directivity
- Maximal rejection of side noise
- Switchable "Low Cut" filter minimizes wind noise
- Phantom or battery powering
- Battery switch with "Low Batt" indicator

