

Product Spec Sheet from Rentex

Chauvet FlareCON Air D-Fi Controller

Download Spec Sheet @ www.rentex.com/spec/LIT0320.pdf

Rentex Product No. LIT0320



Mfr Part No. FLARECON-AIR

The FlareCON Air utilizes cell phones and tablets and turns them into wireless DMX controllers. The built-in Wi-Fi transmitter connects with cell phones and tablets running the FREE FlareCON app, to allow the user to control the connected lighting fixtures. The FlareCON Air then converts the Wi-Fi signal from the phone or tablet into D-Fi and wirelessly transmits those signals to an unlimited number of receivers. The FlareCON app is available for both Android and iOS® in both phone and tablet versions. The FlareCON Air can also connect directly to a DMX controller to send wireless signals out to an unlimited number of D-Fi lights or receivers

Features

- Compact, easy-to-use Wi-Fi receiver and wireless D-Fi transmitter in a single unit
- Compatible with Android™ operating system and Mac OS® on both smartphones and tablets
- Output can be used in wireless D-Fi and/or wired DMX protocols
- Wirelessly synchronize an unlimited number of D-Fi ready fixtures and receivers simultaneously
- Built-in options include manual or automatic channel selection

Detailed Specifications

DMX Channels	512
DMX Connectors	3-pin XLR
Input Voltage	9 VDC, 500 mA (external power supply: 100 to 240 VAC, 50/60 Hz)
Power and Current	4 W, 0.1 A @ 120 V, 60 Hz 4 W, 0.1 A @ 230 V, 50 Hz
Weight	1.2 lbs (0.6 kg)
Dimensions	5.59 x 3.58 x 1.81 in (142 x 91 x 46 mm)