

# Soundcraft EPM6 Spec Sheet from Rentex

## 6-Channel Analog Mixer

(800) 545.2313  
www.rentex.com



Soundcraft®  
by HARMAN

Mfr No. RW5734US

Rentex No. MXR0700

### FEATURES

- True, professional +48V phantom power for condenser microphones
- Professional insert points for external processing
- 6, 8 and 12 mono input channel frame sizes, each with two stereo inputs
- 2 Aux sends, each globally switchable pre or post-fade
- Has GB30 Mic amps, featuring high-resolution adjustment over a wide gain range of 55dB, providing +22dB headroom through the console

The Soundcraft EPM Series provides a straight-forward, yet professional alternative to complex audio mixers. The EPM 6 subrental features 6 mono and 2 stereo input channels providing flexibility.. All mono inputs feature 1/4" phone line and balanced XLR microphone inputs. The famed GB30 microphone preamps provide the quiet, detailed signal synonymous with Soundcraft's large FOH consoles. The stereo inputs provide L/R 1/4" phone connections and are ideal for connecting stereo devices such as keyboards, returning effects, etc.

Type	Analog
Channels	8 (6 Mono 2 Stereo)
Inputs - Mic Preamps	6 x XLR
Inputs - Line	10 x TRS
Inputs - Other	6 x TRS (Insert)
Outputs - Main	2 x XLR
Outputs - Direct	2 x TRS
Outputs - Other	2 x TRS (Monitor), 2 x stereo RCA, 2 x TRS (Aux)
Headphones	1 x 1/4"
Weight	11.02 lbs.
Dimensions (H x W x D)	3.56" x 11" x 14.25"



**RENTEX**  
Audio Visual & Computer Rentals "Since 1980"

24/7/365 Sales & Technical Support

☎ (800) 545.2313

🌐 www.rentex.com