



Mfr No. V-1SDI Rentex No. XVS4050

Roland's V-1SDI Video Switcher is a flexible and versatile video switcher that makes it easy to connect and switch professional 3G SDI cameras and playback sources along with HDMI sources including cameras, smart phones, computers, tablets, Blu-ray players. Compact and portable, the V-1SDI delivers professional switching results with its easy to use hardware interface complete with T-Fader and easy-to-see backlit buttons. With support for 3G-SDI, the V-1SDI can operate at full 1080p resolution and can take advantage of the longer cable distance of SDI making this compact solution suitable for events and applications in even large spaces with the most professional level of SDI camera sources.

Video Processing	8-bit 4:2:2 (YPbPr)
Audio Processing	24-bit at 48 kHz
Video Input Connectors	3 x SDI, BNC 2 x HDMI Type-A
Audio Input Connectors	Analog: RCA phono Mic: Stereo mini jack
Output Connectors	Program 1 x SDI, BNC Preview 1 x SDI, BNC Multiview 1 x HDMI Type-A Audio Analog: RCA phono Headphones: Stereo mini jack
Power Supply (AC)	AC adapter
Current Draw	2.1 A
Power Consumption	25 W
Operating Temperature	32 to 104°F / 0 to 40°C
Dimensions (W x D x H)	12.3 x 4.3 x 2.3" / 31.3 x 10.8 x 5.9 cm
Weight	2.6 lb / 1.2 kg (excluding AC adapter)

FEATURES

- Support for SDI and HDMI cameras, smartphones, tablet computers, PC's, etc.
- Supports up to Full HD 1080p
- 3 x SDI Inputs, 2 x HDMI Inputs
- Quad input multi-viewer with source labeling and audio metering
- HDCP Compliant







24/7/365 Sales & Technical Support