



Mfr No. CL5
Rentex No. MXR7200

FEATURES

- 72 Mono, 8 Stereo Inputs
- 32 Channels and 2 Master Fader
- Built-in Meter bridge
- Built-in Dante interface plus 3 MY-card slots for digital expansion
- Stainless steel stay for iPad support

The Yamaha CL5 digital mixer delivers outstanding sound quality and impressive show control. Connect Rio series stage boxes for up to 72 mono and eight stereo mixable channels, with 32 channel faders and two master faders for control. Built-in Virtual Circuitry Modeling created by Rupert Neve Designs gives you access to Neve Portico 5033 EQ and Portico 5043 compressor/limiter processors, plus other spot-on emulations of classic hardware processors. And built-in Dan Dugan automatic mixing makes it easy for any operator to optimize microphones and effectively fight feedback.

Type	Digital
Channels	32 + 2 master faders, 72 mono channel mixing plus 8 stereo channels
Inputs - Mic Preamps	8 x XLR
Phantom Power	8
Inputs - Digital	2 x RJ-45 (Dante)
Outputs - Digital	2 x RJ-45 (Dante), 1 x XLR (AES/EBU)
Outputs - Other	8 x XLR (line out)
DAW Control	Yes (via Dante)
Channel Inserts	Internal
Talkback	1 x XLR
Busses/Groups	16 send Mix bus, 8 send Matrix bus
Headphones	1 x 1/4"
Weight	79.4 lbs.
Dimensions (H x W x D)	11.75"x 41.5"x 26.25"

