



Mfr No. LW-100P-02
Rentex No. COMLEW2

The Listen Everywhere server can stream audio wirelessly over Wi-Fi to a free mobile app, when accompanied with our standalone network kit or tied into an existing network. The server can support 1000 users with clear reliable audio, making it a versatile multi-channel assistive listening device for HOW, conferences, multi-viewing source events, outdoor drive-in events, and language interpretation. The Server also allows for client customization for branding, messages, and videos to be displayed on the app.

FEATURES

- Connect to your existing Wi-Fi network and stream directly to users through the free mobile app
- Cloud-based management allows for simple management of the system, including updates and customization options
- Up to 1000 users
- 2-Channels
- Low Latency

Connector	5 VDC Barrel
Input Voltage	100-240 VAC, 50-60Hz
Output Voltage	5 VDC
Power	30 W
Audio Inputs	Terminal Block: Two analog inputs, rear panel, one terminal block connector per input, balanced, +4 dBu (line) nominal input level, +16 dBu maximum input level, impedance 100k ohm
Audio Inputs	RCA: Two analog inputs, rear panel, one dual summing RCA connector per input, unbalanced, -10 dBu (line) nominal input level, +2 dBu maximum input level, impedance 100k ohm
Audio Inputs	*Stereo operation requires the use of both inputs
Ethernet	RJ-45 supports 10/100/1000 Mbps speed. Green LED flashes at 100 Mbps, Yellow LED flashes at 1000 Mbps.
USB	Type A 2.0 (female)
Dimensions	1.77in x 6.69in x 3.94in
Weight	.59 kg (1.3 lbs)

